RFT RECORDING THERMOMETER

BASIC RFT	MODEL		R F	0	1		0
CHART DRI	VEC /Course						
	AE2 (COOU!	er Clockwise Rotation)				 _	
Description	0411	Code					
125V/60Hz	24 H	01					
125V/60Hz	7 D	02					- 1
125V/60Hz	12 H	03					
125V/60Hz	48 H	04					
125V/50Hz	24 H	05					-
125V/50Hz	7 D	06					
Spring	24 H	07					.
Spring	7 D	08					
250V/50Hz	24 H	09					
250V/50Hz	7 D	10					
250V/60Hz	24 H	11					
ACCESSORI	ES					 	
Description None		Code					

HOW TO ORDER

Pressure Sensitive Marking Sys.

First select the proper ordering number for the RFT unit. Next consult element selection matrix, see Page 62. Select chart number, see page 70 and 71, and specify as a separate line item. The chart selected must correspond to specific range of sensing element selected. The RFT instrument requires a hollow (L-Type) element plunger (code 51 or 52). High ambient temperature head assembly (code 51) is used when the instrument will be located in ambient temperatures between 32°F but not greater than 150°F. Low ambient head assembly should be called out (code 52) when the instrument will be located in ambient temperatures between -30°F and 125°F. If the solution the sensing bulb is being immersed in is of a corrosive nature, see Form 3052, "Guide for use in Corrosive Applications".

Note: Availability of charts will limit element selection.

Sample Order:

<u>Description</u> Required Number

RFT Unit RF01010

with charts 00208004 (from page 71)

with element 109510520 (from page 62 and 63)

For pricing see Form 3028, Mechanical Price Book, page 12.

Description

Records temperature on a 10" chart. Twelve ambient compensated ranges within -30° to 1100°F, permit application diversity from refrigeration to high temperature ovens. Standard clock rotations 12, 24, and 48 hour, 7 day, others available. Choice of electric or spring wound chart drives available. Wall mounted (brackets furnished) or flush mounted. UL listed.

Operation

Pen recording is powered by the Piston Pak thermal sensing element, which is field replaceable. Temperature ranges may be substituted at any time by obtaining the correct Piston Pak assembly and proper chart graph, and exchange these with those already on the recorder, providing field range changeability.

Recorders

Specifications

Dimensions 15 1/8" W x 13 13/16"H x 4 7/8" D

Chart Diameter 10 inch.

Chart Marking Felt Tip Cartridge/optional pressure sensitive charts

Chart Drive Electric with toggle switch, or spring wound.

Chart Rotation Periods 24 and 48 hour, 7 day, other options.

Flush Mount Cutout 13 1/2" W x 12 11/16" H

Surface Mounting Mounting brackets included.

Electrical Hookup Terminal block accessible with cover open.

One 7/8 inch diameter hole on each side of the case for 1/2 inch Conduit Openings

conduit fitting; drill guide hole spotted in the rear of the case

showing optional rear opening location.

Rated Accuracy 1% of element range.

Agency Listing UL

Warranty One year, see page 80 for details.

Approx. Net Weight*

9 lbs.

Approx Ship. Weight* 14 lbs.

*Weight may vary depending on element length.



RF15-79 RECORDING TEMPERATURE CONTROL

BASIC RF15	-79 MODE		R	F	0	2		
		of #79. It must be						
ordered separatel #73 Close (1/2%)	-							
							I	- 1
CHART DRIV	ES (Count	er Clockwise Rotat	ion) ——				J	
CHART DRIV	ES (Count	er Clockwise Rotat Code	ion) ——				_	
	ES (Count		ion)				J	
Description	·	Code	ion)				_	
Description 125V/60Hz	24 H	Code 01	ion)				1	
Description 125V/60Hz 125V/60Hz	24 H 7 D	Code 01 02	ion)				1	
Description 125V/60Hz 125V/60Hz 125V/60Hz	24 H 7 D 12 H	Code 01 02 03	ion)				1	
Description 125V/60Hz 125V/60Hz 125V/60Hz 125V/60Hz	24 H 7 D 12 H 48 H	Code 01 02 03 04	ion)				1	
Description 125V/60Hz 125V/60Hz 125V/60Hz 125V/60Hz 125V/50Hz 125V/50Hz	24 H 7 D 12 H 48 H 24 H	Code 01 02 03 04 05	ion)				1	
Description 125V/60Hz 125V/60Hz 125V/60Hz 125V/60Hz 125V/50Hz 125V/50Hz Spring wound	24 H 7 D 12 H 48 H 24 H 7 D	Code 01 02 03 04 05 06	ion)				1	
Description 125V/60Hz 125V/60Hz 125V/60Hz 125V/60Hz 125V/50Hz 125V/50Hz	24 H 7 D 12 H 48 H 24 H 7 D 24 H	Code 01 02 03 04 05 06	ion)					
Description 125V/60Hz 125V/60Hz 125V/60Hz 125V/60Hz 125V/50Hz 125V/50Hz Spring wound Spring wound	24 H 7 D 12 H 48 H 24 H 7 D 24 H 7 D	Code 01 02 03 04 05 06 07	ion)				1	

ACCESSORIES

Description	Code
None	0
257AP Low Limit Switch	1
Pressure Sensitive Marking Sys	3

HOW TO ORDER

First select the proper ordering number for the RF15-79 unit. Next consult element selection matrix, see Page 62. Select chart number, see page 70 and 71, and specify as a separate line item. The chart selected must correspond to specific range of sensing element selected. The RF15-79 instrument requires a hollow (L-Type) element plunger (code 51 or 52). High ambient temperature head assembly (code 51) is used when the instrument will be located in ambient temperatures between 32°F but not greater than 150°F. Low ambient head assembly should be called out (code 52) when the instrument will be located in ambient temperatures between -30°F and 125°F. If the solution the sensing bulb is being immersed in is of a corrosive nature, see Form 3052, "Guide for use in Corrosive Applications".

Note: Availability of charts will limit element selection.

Sample Order:

Description RF15-79 Unit **Required Number**

RF02010

with charts with element 00208004 (from page 71)

109510520 (from page 62 and 63)

For pricing see Form 3028, Mechanical Price Book, page 12.

Description

This recording temperature controller incorporates two switches which operate in fixed relationship to the temperature setting. Differential between switches can be adjusted up to 5% of scale range. Like other RF series recorders, this unit has a 10" chart, may be flush or surface mounted. Unit is shipped with brackets for surface mounting operation. UL and CSA listed.

Operation

This unit incorporates two snap-setting switches mounted on a common setting arm (red pointer) and actuated by the same temperature response mechanism which moves the recording pen.

First to be actuated on a temperature rise is a leaf-type switch. The second, a pin-type switch, is actuated only when the recorded temperature exceeds the operation of the first switch.

Switches are mounted one behind the other, each having its own circuit. Temperature actuation points between the two switches (differential) is adjustable from 0 to 5 percent of scale range, with tolerance on switch settings \pm 1/2%. Adjustment is made by set screws inside the instrument case.

Specifications

Dimensions 15 1/8" W x 13 3/16"H x 4 7/8" D

Chart Diameter 10 inch.

Chart Marking Felt Tip Cartridge/optional pressure sensitive charts

Chart Drive Electric with toggle switch, or spring wound.

Chart Rotation Periods 24 and 48 hour, 7 day, other options.

Panel Mount Cutout 13 1/2" W x 12 5/8" H

Surface Mounting Mounting brackets included.

Switch Type Three wire SPDT, 2 per mechanism.

Switch Sensitivities Normal 1% of range (#79) standard.

Super Sensitive (#73) 0.5% of range optional.

Electrical Hookup Terminal block accessible with cover open.

Conduit Openings One 7/8 inch diameter hole on each side of the case for 1/2 inch

conduit fitting; drill guide hole spotted in the rear of the case

showing optional rear opening location.

Electrical Rating 50VA, inductive; 500VA, non inductive; 250V maximum AC only.


Agency Listings UL and CSA.

Warranty One year, see page 80 for details.

Approx. Net Weight* 9 lbs.
Approx Ship. Weight* 14 lbs.

*Weight may vary depending on element length.

Recorders



RFA - PNEUMATIC RECORDING TEMPERATURE CONTROLLER

BASIC RFA MODEL		•		R F	0	3		0
CHART DRI	VES (Counter	Clockwise	Rotation)					
125V/60Hz	24 H	01						
125V/60Hz	7 D	02						
125V/60Hz	12 H	03						
125V/60Hz	48 H	04						
125V/50Hz	24 H	05						
125V/50Hz	7 D	06						
Spring	24 H	07						
Spring	7 D	08						
250V/50Hz	24 H	09						
250V/50Hz	7 D	10						
250V/60Hz	24 H	11						
ACCESSORI	ES							
Description		Code						

HOW TO ORDER

Pressure Sensitive Marking Sys.

First select the proper ordering number for the RFT unit. Next consult element selection matrix, see Page 62. Select chart number, see page 70 and 71, and specify as a separate line item. The chart selected must correspond to specific range of sensing element selected. The RFT instrument requires a hollow (L-Type) element plunger (code 51 or 52). High ambient temperature head assembly (code 51) is used when the instrument will be located in ambient temperatures between 32°F but not greater than 150°F. Low ambient head assembly should be called out (code 52) when the instrument will be located in ambient temperatures between -30°F and 125°F. If the solution the sensing bulb is being immersed in is of a corrosive nature, see Form 3052, "Guide for use in Corrosive Applications".

0

3

Note: Availability of charts will limit element selection.

Sample Order:

<u>Description</u> Required Number

RFA Unit RF03010

with charts 00208004 (from page 71)

with element 109510520 (from apge 62 and 63)

For pricing see Form 3028, Mechanical Price Book, page 12.

Description

This recorder is an accurate, sensitive pneumatic controller used in conjunction with an air-operated valve for control of steam, gas or fuel for combustion equipment or to operate other pneumatic devices. Requires approximately 16 psi input, air output is 3 to 15 psi, throttling span is 5% to 25% of scale range. Flush or wall mounted (brackets supplied) with 12 optional ranges from -30°F to 1100°F.

Operation

Operates in an adjustable throttling range of 5-25% of scale range. As the indicating pointer, moving up or down scale in response to the expansion or contraction in the thermal sensing element, enters the throttling range and approaches set point, it changes the effective orifice in the instrument's bleed valve.

Depending upon its control action (reverse or direct acting) this increases or decreases the pressure delivered to the remotely-placed air operated control device.

Pressure transmitted by the control instrument is reflected by the valve position of the airoperated device which modulates the flow of heating or cooling medium.

Load error, inherent in throttling controls, is compensated by manual reset adjustment. Note: For long air line feeds, ie. 10 feet or greater, or large volume air valves or control devices, an air pressure booster relay is strongly recommended.

Specifications

Dimensions 15 1/8" W x 13 3/16"H x 4 7/8" D

Chart Diameter 10 inch.

Chart Marking Felt Tip Cartridge/optional pressure sensitive charts

Chart Drive Electric with toggle switch, or spring wound.

Chart Rotation Periods 24 and 48 hour, 7 day, other options.

Flush Mount Cutout 13 1/2" W x 12 11/16" H
Surface Mounting Mounting brackets included.

Electrical Hookup Terminal block accessible with cover open.

Conduit Openings One 7/8 inch diameter hole on each side of the case for 1/2 inch

conduit fitting; drill guide hole spotted in the rear of the case

showing optional rear opening location.

Air Hookup 1/4-NPT inlet and outlet openings at top and back of case.

Air Input Requirements Approximately 16 psi to 20 psi.

Air Output Pressure 3 to 15 psi.
Air Consumption 12 cfh maximum.

Throttling Span Adjustable from 7 to 35% of element range. Load Error Adjustment Manual reset for load error compensation.

Control Action Reverse or Direct Acting (factory set-reverse, field changeable to

direct acting).


Air Gauges Inlet and outlet - both gauges provide for English and Metric

scales.

Warranty One year, see page 80 for details.

Approx. Net Weight* 9 1/2 lbs.
Approx Ship. Weight* 10 3/4 lbs.

^{*}Weight may vary depending on element length.



Recorders

RFP MODULATING TEMPERATURE RECORDER

		_	R	F	0	4		
BASIC RFP I	MODEL							
The potentiometer	er coil kits listed be	elow are available.					1	
They must be ord	lered separately a	nd installed in the field.						
Description	Part #							
100 Ohm 1/8"	64403504							
100 Ohm 5/16" 135 Ohm 1/8"	64403505 64403501							
		•						
CHART DRIV	ES (Counte	Clockwise Rotation					J	
Description		Code						
125V/60Hz	24 H	01						
125V/60Hz	7 D	02						
125V/60Hz	12 H	03						
125V/60Hz	48 H	04						
125V/50Hz	24 H	05						
125V/50Hz	7 D	06						
Spring wound	24 H	07						
Spring wound	7 D	08						
250V/50Hz	24 H	09						
250V/50Hz	7 D	10						
250V/60Hz	24 H	11						
		_						
ACCESSORIE	S							

None 0
Pressure Sensitive Marking Sys. 3

HOW TO ORDER

First select the proper ordering number for the RFP unit. Next consult element selection matrix, see Page 62. Select chart number, see page 70 and 71, and specify as a separate line item. The chart selected must correspond to specific range of sensing element selected. The RFP instrument requires a hollow (L-Type) element plunger (code 51 or 52). High ambient temperature head assembly (code 51) is used when the instrument will be located in ambient temperatures between 32°F but not greater than 150°F. Low ambient head assembly should be called out (code 52) when the instrument will be located in ambient temperatures between -30°F and 125°F. If the solution the sensing bulb is being immersed in is of a corrosive nature, see Form 3052, "Guide for use in Corrosive Applications".

Note: Availability of charts will limit element selection.

Sample Order:

<u>Description</u> Required Number

RFP Unit RF04010

with charts 00208004 (from page 71)

with element 109510520 (from page 62 and 63)

For pricing see Form 3028, Mechanical Price Book, page 12.

Description

This recorder is a potentiometer-type controller designed for use with proportional positioning motors to operate modulating valves or damper systems where extremely close sensitivity or straight-line control is required.

The instrument automatically positions any of a variety of standard motor operators to provide precise temperature control without sawtooth line characteristics of conventional on-off control. Flush or wall mounted, brackets supplied. Available in 12 optional ranges from -30°F to 1100°F. CSA listed.

Recorders

Operation

The potentiometer coil, which moves up or down scale in response to the expansion or contraction in the thermal element, also slides the contact finger along the potentiometer coil within the modulating range.

In essence, the coil forms half of a Wheatstone Bridge circuit, while the other half of the bridge is formed by a potentiometer of similar electrical characteristics built into the proportioning motor and driven by the motor shaft.

When the contact finger is located at the low end of the potentiometer coil as in process start-up, the motor drives the device to the fully open position.

With the contact finger at the high end of the coil, the motor moves the drive to the fully closed position.

Specifications

Dimensions

15 1/8" W x 13 3/16"H x 4 7/8" D

Chart Diameter

10 inch.

Chart Marking

Felt Tip Cartridge/optional pressure sensitive charts

Chart Drive

Electric with toggle switch, or spring wound.

Chart Rotation Periods

24 and 48 hour, 7 day, other options.

Flush Mount Cutout Surface Mounting 13 1/2" W x 12 11/16" H

Electrical Hookup

Mounting brackets included.

Conduit Openings

Terminal block accessible with hinged cover open. One 7/8 inch diameter hole on each side of the case for 1/2 inch

conduit fitting; drill guide hole spotted in the rear of the case

showing optional rear opening location.

Coil Resistance

135 ohms 5/16" width std; others available as field installable kits.

Electrical Rating

Max. volts - 30; max. watts - 3.

Coil Length.

5/16"

1/8"

5/8"

Throttling Range Available

12%

5%

24%

Rated Accuracy

1% of element range.

Agency Listing

CSA

Warranty

One year, see page 80 for details.

Approx. Net Weight*

12 lbs.

Approx Ship. Weight*

17 lbs.

^{*}Weight may vary depending on element length.

